

Product Name :
Physics Lab Multimeter, Digital

Product Code :
NLAB-EDUSCHOOLEQ158066



Description :

Physics Lab Multimeter, Digital

Technical Specification :

A Digital Multimeter is a test tool used to measure two or more electrical values principally voltage (volts), current (amps) and resistance (ohms).

It is a standard diagnostic tool for technicians in the electrical industries

3½ Digits Manual Ranging, Temperature Measurement, Continuity Buzzer/Diode Test, hFE Test, Data Hold function, DC voltage range: 200mV, 2000mV, 20V, 200V, 250V

Best Accuracy: $\pm(0.5\%rdg + 2 \text{ digits})$

AC voltage range: 200V, 250V

Best Accuracy: $\pm(1.2\%rdg + 3 \text{ digits})$, DC current range: 2000microA, 20mA, 200mA, 10A, Best Accuracy: $\pm(1.0\%rdg + 2 \text{ digits})$

Resistance range: 200 ~ 20M 6 ranges, Best Accuracy: $\pm(0.8\%rdg + 5 \text{ digits})$, Open circuit voltage: 2.3V

Buzzer sounds if conductance less than 100hm

Operating voltage: DC 9V battery

Naugralabequipments

Website: www.naugralabequipments.com, **Email:** sales@naugralabequipments.com

Address: 6148/6, Guru Nanak Marg, Ambala Cantt, Haryana, India. **Phone:** +91-9896600003