

Product Name :
Digital Watt Meter

Product Code :
NLAB-TESTINGLABM19004

Description :

Digital Watt Meter

Technical Specification :

Features :

LSI-circuit provides high reliability & durability

Measurement : Watt, ACV, ACA and Power factor

21.8 x 8.5mm large LCD and Max. reading 9999

Fully Auto range and zero adjustment facility

Memory record, recall and data hold function

Built in low battery indicator

Technical Specifications :

Watt (True power) : 0 ~ 6000 W

Accuracy : $\pm(1\%+5W)$, Resolution : 1W

ACV (True RMS) Range : 0 ~ 600V

Accuracy : $\pm(0.3\% + 0.3V)$ Resolution : 0.1V

ACV input impedance : 10M Ω ,

ACA (True RMS) range : 0.01 ~ 10A

Accuracy : $\pm(0.3\% + 0.03A)$ Resolution : 0.01A

Power factor range : 0.01 ~ 1.00

Accuracy : $\pm(1\% + 2d)$, Resolution : 0.01

Data output : RS 232 / USB PC interface

Sampling time : Approx. 1 second

Dual value display with backlight facility

Power : DC 9 V Battery

Naugralabequipments

Website: www.naugralabequipments.com, **Email:** sales@naugralabequipments.com

Address: 6148/6, Guru Nanak Marg, Ambala Cantt, Haryana, India. **Phone:** +91-9896600003